RefDes	Value	Description	Marking				#
C1,2,3,4	18n	Cap, 0.2"	183K				4
C5	100n	Cap, 0.2"	104K				1
C6,7,8	10u	Polarized Cap, 0.2"	10uF or 47uF	16V	black band (-)		3
R16,17,18, 19	100	1/8W Resistor	brown	black	brown	gold	4
R2,R4**	120	1/8W Resistor	brown	red	brown	gold	2
R3,R32*	680	1/8W Resistor	blue	grey	brown	gold	1
R1*,10,11,12,13	1k	1/8W Resistor	brown	black	red	gold	4
R5,6,7,8,9,14,15	10k	1/8W Resistor	brown	black	orange	gold	7
D1**		1N4148	(not included)				
J1		1/8" Stereo Headphone Jack					1
J2		MMC/SD Card Socket					1
J3		Miniature DIN Connector					1
J4		RCA Jack (yellow)					1
J5		VGA connector **	(not included)				
U1		Dual Op Amp	MCP602-I/P or MCP6022-I/P				1

Basic PIC24 configuration: mount R3, do not mount R32 and R1
*)Advanced PIC24 and PIC32 configuration: mount R32 and R1, do not mount R3
**)VGA configuration: mount R32 and R1, do not mount R3, replace R4 with diode 1N4148, mount VGA connector J5

Thank you for your order, please don't hesitate to contact me if you have any problem or doubt on the board assembly.
Hope you will have a great time!

Lucio Di Jasio
(the pilot)
mailto: pilot@flyingpic24.com
mailto: lucio@exploringpic32.com